

- 2 – POTS, ALPHA A500K, 3/8 BUSHING
- 2 - 4PDT “ON-ON-ON” MODE SWITCHES  
SALECOM T80T845-ZBQE-H
- 2 – 100K ¼ WATT RESISTORS, CARBON FILM
- 2 – 152J CAPACITORS, MYLAR
- 1 – PICKUP SELECTOR TOGGLE, 15/32 X 32  
BUSHING
- 1 – 153J TONE CAPACITOR, MYLAR
- 1 – OPEN FRAME OUTPUT JACK

- CHANGES FROM REV A:**
- ★ TONE CONTROL FEED MOVED TO  
WIPER OF VOLUME POT

SINGLE CONDUCTOR SHIELDED WIRE  
(WITH VINYL INSULATING TUBING)

4 CONDUCTOR CABLE  
(BLUE = BARE WIRE/SHIELD)


INSULATING TUBING

SOLDERED CONNECTION

SOLDER BRIDGE GROUND  
TO BACK OF VOLUME POT

SALECOM T80T845-ZBQE-H  
NOTCH “DOWN”

SEE SHEET 2  
FOR SWITCH  
WIRING  
DETAIL




CONFIDENTIAL DOCUMENT				G-ROK			
MATERIAL				TITLE 55 SERIES HARNESS			
FINISH				PART NO.			
COLORS				DRAWN BY KIRKLAND			
DIMENSIONS MILLIMETERS		LINEAR TOLERANCE .XX ± 0.13		REV B	DATE 17AUG2010		
ANGLE TOLERANCE ± .5°		.XXX ± 0.013		SIZE	SCALE 1:1	SHEET 1	OF 2


CoAxe Mode Switch Wiring for SALECOM 4PDT

- 1. Capacitors, resistors, jumpers, and pickup selector cable installed.  
*Components:*  
(2) 4PDT On-On-On Switches, SALECOM T80T845-ZBQE-H  
(2) 100K ¼ watt 5% Carbon Film Resistors  
(2) 1500pF 50V 5% Radial Mylar Film Capacitors  
(2) insulated jumpers

4-conductor shielded cable (No shield connection on mode switch.)



- 2. Pickups cables installed.  
(Shield wire shown in blue.)



**CONFIDENTIAL  
DOCUMENT**

**G-ROK**

MATERIAL		TITLE	
FINISH		55 SERIES HARNESS	
COLORS		PART NO.	
DIMENSIONS		DRAWN BY	
MILLIMETERS		KIRKLAND	
LINEAR TOLERANCE		REV	DATE
.XX ± 0.13		B	17AUG2010
ANGLE TOLERANCE		SIZE	SCALE
± .5°		.XXX ± 0.013	1:1
		SHEET	2 OF 2